

安全警告

● 警告符号的要点



表示潜在的危险情况，如不加以防止，很可能导致轻度或中度的人身伤害，或财产损坏。在使用该产品前应仔细阅读本手册。

● 警告符号

△ 警告

当电源带电时，不要接触端子。这样做很可能会因为电击导致轻度伤害。

电源切断后1分钟之内，不要接触端子。这样做很可能会因为电击导致轻度伤害。

不要将该产品用于有易燃易爆气体的场合。否则有可能因为爆炸而造成轻度伤害。

不允许金属碎片、导线线头或者安装时产生的细小的金属屑进入设备。这样做很可能导致电击、火灾或机器的故障。

绝对不要拆卸、改装以及修理该产品或接触任何内部元件。有时会发

生轻微的电击、火花或误动作。

如果输出继电器超过了预期的使用寿命，有时会发生触点融化和燃

烧。始终要注意输出继电器的应用环境，并在额定负载及预期寿命以

内使用。输出继电器的预期寿命随着输出负载以及开关条件的变化而变化。

使用规定的力矩拧紧端子螺丝。松动的螺丝可能导致火灾。

安全上のご注意

● 警告表示の意味



正しい取扱いをしなければ、この危険のために、時に軽傷・中程度の傷害を負ったり、あるいは物的損害を受ける恐れがあります。お使いになる前にこの取扱説明書をお読みになり、十分ご理解ください。

● 警告表示

△ 注意

感電により軽度の傷害が稀に起こる恐れがあります。通電中は端子に触らないでください。

感電により軽度の傷害が稀に起こる恐れがあります。電源を切った後、1分以内は端子に触らないでください。

爆発により、稀に軽度の傷害の恐れがあります。引火性、爆発性ガスのある所では使用しないでください。

軽度の感電、発火、機器の故障が稀に起こる恐れがあります。製品の中に金属、導線または取り付け加工中の切粉などが入らないようにしてください。

軽度の感電、発火、機器の故障が稀に起こる恐れがあります。分解、改造、修理したり、内部に触らないでください。

寿命を超えた状態で使用すると接点溶着や焼損が稀に起こる恐れがあります。必ず実使用条件を考慮し、定格負荷、電気的寿命回数内でご使用ください。出力リレーの寿命は、開閉容量、開閉条件により大きく異なります。

ねじが緩むと、発火が稀に起こる恐れがあります。端子ネジは規定トルクで締めてください。

安全使用注意事项

了解以下警告以避免操作失误、误动作或产品特性、功能的相反效果。如果不这样做，可能导致不可预期的事情发生。

1) 该产品只被设计为室内使用。不要将该产品用在室外或者下列地点。

- 直接接受加热设备热辐射的地方。
 - 有液体或油气飞溅的地方。
 - 阳光直射的地方。
 - 灰尘较多或有腐蚀性气体（特别是硫化物气体和氨气）的地方。
 - 温度剧烈变化的地方。
 - 结冰和结露的地方。
 - 有震动或大的冲击的地方。
 - 有挥发性、易燃性气体的地方。
- 2) 在额定的温度和湿度范围内使用/存储该设备。必要时应采取强制冷却。
- 3) 按端子的极性进行正确的接线。
- 4) 不用的端子不要接线。
- 5) 在控制器与可以产生高频或浪涌或产生大量静电的设备之间应保持足够远的距离。将高压或大电流导线与其它导线隔离，在端子接线时避免与电源线共端或并联。
- 6) 在该产品的附近应该有开关或者断路器。开关或者断路器应该在操作者便于够到的地方，并且有明显的断开标志。
- 7) 不要使用油漆稀释剂或同类化学品清洁该产品。使用标准等级的酒精。
- 8) 请在确认是否是您所希望的产品之后，再行使用。
- 9) 请在额定范围内保存。如在-10°C以下保存后使用时，请于常温下放置三小时后再通电。

使用的适用性

欧姆龙不负责遵守任何使用该产品进行集成的用户产品的标准、章程或规则。采取一切必要的步骤来决定该产品对采用该产品的系统、机器和设备的适用性。

了解并遵守一切使用该产品的禁止行为。

如果应用该产品的系统在设计上不能保证有效处理对生命、财产的危害，不要在这样的系统上使用该产品。在整套装备或系统中适当使用和安装欧姆龙产品。

参见产品目录中有关保证和免责声明。

使用注意事项

- 1) 在额定负载和供电电源下使用该产品。
- 2) 使用开关或继电器触点以确保同时将电源升为额定电压。如果电压是逐渐上升的，电源可能无法复位或者发生输出误动作。

Safety Precautions

● Key to Warning Symbols



Indicates a potentially hazardous situation which, if not avoided, is likely to result in minor or moderate injury or property damage. Read this manual carefully before using the product.

● Warning Symbols

△ CAUTION

Do not touch the terminals while power is being supplied. Doing so many occasionally result in minor injury due to electric shock.

Do not touch the terminals at least within 60 seconds, after turning the power OFF. Doing so many occasionally result in minor injury due to electric shock.

Do not use the product where subject to flammable or explosive gas. Otherwise, minor injury from explosion may occasionally occur.

Do not allow pieces of metal, wire clippings, or fine metallic shavings or filings from installation to enter the product. Doing so many occasionally result in electric shock, fire, or malfunction.

Never disassemble, modify or repair the product or touch any of the internal parts. Minor electric shock, fire, or malfunction may occasionally occur.

If the output relays are used past their life expectancy, contact fusing or burning may occasionally occur. Always consider the application conditions and use the output relays within their rated load and electrical life expectancy.

The life expectancy of output relays varies considerably with the output load and switching conditions.

Tighten the terminal screws at the specified torque. Loose screws may occasionally result in fire.

Precautions for Safety Use

Be sure to observe the following precautions to prevent operation failure, malfunction, or adverse affects on the performance and functions of the product. Not doing so may occasionally result in unexpected events.

- 1) The product is designed for indoor use only. Do not use the product outdoors or in any of the following locations.
 - Places directly subject to heat radiated from heating equipment.
 - Places subject to splashing water, oil or chemicals.
 - Places subject to direct sunlight.
 - Places subject to dust or corrosive gas (in particular, sulfide gas and ammonia gas).
 - Places subject to intense temperature change.
 - Places subject to icing and condensation.
 - Places subject to vibration and large shocks.
 - Places subject to explosive or flammable gases.
- 2) Use/store within the rated temperature and humidity ranges. Provide forced-cooling if required.
- 3) Be sure to wire properly with correct polarity of terminals.
- 4) Do not wire the terminals which are not used.
- 5) Allow as much space as possible between the controller and devices that generate a powerful high frequency, surge or much static electricity. Separate the high-voltage or large-current power lines from other lines, and avoid parallel or common wiring with the power lines when you are wiring to the terminals.
- 6) A switch or circuit breaker should be provided close to this unit. The switch or circuit breaker should be within easy reach of the operator, and must be marked as a disconnecting means for this unit.
- 7) Do not use paint thinner or similar chemical to clean with. Use standard grade alcohol.
- 8) Make sure the proper product is specified for the application.
- 9) Store at the specified temperature. If the products has been stored at a temperature of less than -10°C, allow the products to stand at room temperature for at least 3 hours before use.

Suitability For Use

OMRON shall not be responsible for conformity with any standards, codes, or any regulations that apply to the combination of the products in the customer's application or use of the product.

Take all necessary steps to determine the suitability of the product for the systems, machines, and equipment with which it will be used.

Know and observe all prohibitions of use applicable to this product.

NEVER USE THE PRODUCTS FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISK, AND THAT THE OMRON PRODUCT IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

See also product catalogue for Warranty and Limitation of Liability.

Precautions for Correct Use

- 1) Use this product within the rated load and power supply.
- 2) Make sure that the rated voltage is attained at the moment of turning ON the power using a switch or relay contact. If the voltage is applied gradually, the power may not be reset or output malfunctions may occur.

联系方式

欧姆龙(中国)有限公司

电话 : 010-83913005

欧姆龙(中国)有限公司武汉办事处

电话 : 027-65776566

欧姆龙(中国)有限公司苏州办事处

电话 : 0512-8669277

台湾欧姆龙股份有限公司(台北)

电话 : 02-27153331

欧姆龙(中国)有限公司重庆办事处

电话 : 023-63803720

欧姆龙(中国)有限公司辽宁办事处

电话 : 024-22566105

欧姆龙(广州)自动化有限公司

电话 : 020-87320508

台湾欧姆龙股份有限公司桃园营业所

电话 : 03-3554463

欧姆龙(中国)有限公司南京办事处

电话 : 025-4726876

欧姆龙(中国)有限公司杭州办事处

电话 : 0571-85271339

欧姆龙(中国)有限公司成都办事处

电话 : 028-6765245

台湾欧姆龙股份有限公司台中营业所

电话 : 04-23250834

欧姆龙(中国)有限公司山东办事处

电话 : 0531-2929765

欧姆龙(中国)有限公司昆明办事处

电话 : 0871-5366019

欧姆龙(中国)有限公司西安办事处

电话 : 029-5381152

台湾欧姆龙股份有限公司台南营业所

电话 : 06-2903797

欧姆龙(中国)有限公司上海办事处

电话 : 021-50372222

欧姆龙亚洲有限公司厦门办事处

电话 : 0592-5117709

歐姆龍亞洲有限公司(香港)

电话 : (852) 23753827

技术咨询

800免费技术咨询电话:800-820-4535(仅限于中国大陆)

制造单位

欧姆龙(上海)有限公司

地 址: 上海市浦东新区金桥出口加工区金吉路789号

邮 编: 201206